


Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android Tablets with 16 MIDAS PRO Preamps, Integrated Wifi Module and Multi-Channel USB Audio Interface

- ⊗ iPad*/Android* tablet controlled 18-input digital mixer for studio and live application
- ⊗ 16 award-winning MIDAS PRO microphone preamplifiers
- ⊗ Built-In Tri-Mode Wifi router for direct operation—no need for external routers
- ⊗ 18 x 18 channel, bidirectional USB 2.0 interface
- ⊗ Dugan*-style Auto-Mixing automatically manages microphone gain sharing
- ⊗ 4 digital signal processing effects engines
- ⊗ ULTRANET connectivity for P-16 Personal Monitoring System*
- ⊗ Rack ears and protection bumpers included for flexible rack and onstage applications
- ⊗ 6 aux and main LR buses with inserts, full dynamics processing and 6-band parametric or 31-band graphic EQ
- ⊗ 6 XLR aux outputs and 2 XLR main outputs plus phones connector
- ⊗ 40 bit floating point digital signal processing
- ⊗ Free iOS, Android and PC/Mac*/Linux* apps available for remote operation via Ethernet, LAN or WiFi
- ⊗ MIDI In/Out allows controlling the mixer via MIDI equipment or for use as a USB MIDI interface
- ⊗ Future firmware updates, incl. new FX "Plug Ins", downloadable from midasconsoles.com free of charge

The **MIDAS M32** completely redefined what is possible from a digital mixer – and thousands of users are enjoying the results. Now that technology has been incorporated into the small but powerful MR18 rack-mountable mixer, which will forever change the way you record and the way you play live music.



about the venue or the tracking room and manipulate all the parameters of your mix, and the performers have the same freedom to dial-in their personal monitor mixes. Advanced engineering and meticulous design combine to deliver professional-grade performance and impressive affordability – the MR18.



A Mixer Whose Time has Come

Over the past few years, the world of recording and performance audio has experienced a major paradigm shift, one that requires musicians and performers alike to take advantage of emerging technologies that offer flexibility and ease of use. The MR18 is an 18-input/8-bus portable mixer housed in a sturdy stage box design for use with iPad and Android tablets. It is ideally suited for both live and studio applications thanks to 16 award-winning **MIDAS PRO** mic preamps, integrated Wifi module for wireless control, MIDI I/O – and a multi-channel, bidirectional USB Audio Interface. Free iOS, Android and PC apps enable you to move

Digital Mixers


MR18

18-Input Digital Mixer for iPad/Android Tablets with 16 MIDAS PRO Preamps, Integrated Wifi Module and Multi-Channel USB Audio Interface

- ⊗ Auto-ranging universal switch-mode power supply
- ⊗ 3-Year Warranty Program*
- ⊗ Designed and engineered in the U.K.

16 MIDAS PRO Mic Preamps


The MIDAS PRO mic amp was developed for the PRO Series mixing consoles and is also found in the M32 – and has been recognised by leading live sound and recording engineers as the very essence of the famous MIDAS sound. It is here in the MR18 that more than 40 years of design excellence has come together with premium grade components to provide unparalleled warmth and depth, subtle ambience, and immaculate spatial positioning – for more precise imaging than competing models. The award-winning MIDAS microphone preamplifier has inspired generations of live sound engineers to their best work, creating sonic landscapes that have captivated audiences worldwide. MR18 comes equipped with 16 MIDAS PRO preamps, all of which are literally ready for your input via the Neutrik combo connectors with locking latches.



*iPad and Mac are trademarks of Apple Inc. Android is a trademark of Google Inc. Linux is the registered trademark of Linus Torvalds in the U.S. and other countries. All third-party trademarks are the property of their respective owners. Their use neither constitutes a claim of the trademark nor affiliation of the trademark owners with MUSIC Group. Product names are mentioned solely as a reference for compatibility, effects and/or components. iPad and P-16 Monitoring System are not included. Warranty details can be found at music-group.com.

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Built-In Tri-Mode Wifi Router

Designed for the ultimate in mobility, the MR18 comes with an integrated Wifi module for direct control of your mixer's functions – without the need to setup and configure an external router. The MR18 gives you the freedom to focus on your mix, while allowing you to move about the venue to experience what every part of the audience is hearing. Plus you can adjust live monitor wedges from the artist's perspective – or better yet, let them mix their own IEMs and floor monitors via their own tablets.

1. Access Point is the easiest way to connect up to 4 clients directly and concurrently (i.e., iPad, Android smartphone/tablet or laptop). This mode should have your remote control up and running in less than a minute.
2. Wifi Client allows you to add your mixer to the existing wireless network where the controlling apps and devices are connected.
3. Alternately, wired connections can be made directly to your PC, to a local area network (LAN), or when connecting to a dedicated Wifi router, e.g., for extended range or 5 GHz applications.

Recording Simplified

The incredibly fast and comprehensive 18 x 18 channel, bi-directional USB interface makes the MR18 an amazingly powerful digital mixing solution for recording directly to your iPad or PC. Dial in the perfect monitoring mix with effects and zero-latency, while sending up to 16 source signals – and the keyboard player's MIDI notes to your DAW for recording and editing.

Whether you are making rock history in the studio, or you want to capture intimate live performances – it has never been easier to record stunning tracks with exceptional clarity.



MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Revolutionary Auto-Mixing

When your application calls for a multiple-microphone setup, such as an onstage panel discussion, press conference or courtroom proceeding, etc., it can become a challenge to maintain so many open mics – and preserve maximum gain and priority for the moderator.

A major first for compact audio mixers, our revolutionary M AIR Gain Sharing technology can easily manage fully automated mixes with up to 16 live microphones. Based on the legendary Dan Dugan automix system, the MR18's gain sharing paradigm automatically controls the levels of all selected microphones in real time, without any gating artifacts or noise modulation.


This function dramatically reduces the typical feedback, studio noise and comb filtering challenges that can occur when two, or more mics are in close proximity of each another. M AIR Gain Sharing technology provides a consistent system gain structure, even when multiple speakers are talking at the same time.

4 Onboard M32 Effects Engines

Equipped with the very same FX engines as the now legendary M32 Digital Mixing Console, the onboard virtual FX Rack provides access to four true-stereo (8 mono), multi-effects processors including delay, chorus, dynamics – plus the MR18 can run production-quality, true-stereo reverbs concurrently with 31-band EQ on the main and aux buses, all without the need for any additional hardware.

You can select any combination of high-end simulations of legendary studio effects, such as the Lexicon 480L and PCM70, as well as the EMT250 and Quantec QRS reverbs. Onboard processing means your computer no longer has to do the heavy lifting during a mixing session with DAW plugins, as the MR18 has a whole studio of FX under its bonnet.

Custom-designed, and physically modeled after some of the most iconic and sought-after processors, all effects run inside the low-latency environment of the M32 mix engine, ensuring flawless performance, flexible routing and the end of cable faults.



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

High-End FX Racks at Your Finger Tips

The immaculate tube signal path in Teletronix' LA-2A Leveling Amplifier has left its exceptional clarity, its rich and warm compression on countless albums of the past decades.



The ultra-smooth optical attenuator is closely modeled in our **LEISURE COMPRESSOR**. It provides breezy, natural and effortlessly musical compression. (Inspired by Teletronix LA-2A*)

When Urei released the 1176LN Limiting Amplifier in the late 60's, it broke new ground. Field Effect Transistors employed were just invented, and the 1176 was one of the first audio processors to benefit from this new technology.



Our digital reincarnation, **ULTIMO COMPRESSOR**, is based on the early Rev. E model, and authentically captures the smooth character of the original Class-A output stage and its FET's legendary fast Attack. (Inspired by Urei 1176LN*)

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

The Fairchild 670 tube compressor not only achieves record bids in high-end vintage gear auctions, it also delivers some of the finest colorations in compressor history. Two small trim VRs preset the control side chain action, a six-step switch determines the timing, and the two large Input and Threshold knobs adjust the levels.



Our **FAIR COMPRESSOR** model is true to the original signal path, and conveniently provides models for dual, stereo-linked or M/S operation. (Inspired by Fairchild 670*)



The **COMBINATOR** is an amazing 5-band compressor that emulates famous broadcasting and mastering compressors. A highly complex processor, the COMBINATOR utilizes automatic parameter control that produces stunning and "inaudible" results. Makeup-gain for each frequency band will automatically be adjusted by the Spectral Balance Control (SBC) function, to maintain a balanced audio spectrum.



The **XTEC EQ1** emulates one of the undisputedly best passive studio equalizers ever manufactured. Virtually indescribable, recording engineers claim the Pultec EQP-1a to be the "secret sauce" of sound enhancement. We analyzed this classic to the core and created an exact physical model that reproduces the multi-faceted sound in painstaking detail. Even the transformers and tube output stage have been faithfully modeled! (Inspired by Pultec EQP-1a*)

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Put simply, Pultec literally wrote the book on passive equalization. By digitally “rebuilding” every aspect of this original classic, we captured the very essence in our mid-range focused parametric equalizer **XTEC EQ5**. Our digital re-incarnation authentically emulates the smooth character of its rather unique components. (Inspired by Pultec MEQ5*)



The new **SUB OCTAVER** provides two channels of earth-shattering sub-harmonics generation, one or even two octaves below the input signal. While originally designed for bass players, the effect can be adjusted for Hi, Mid and Low frequency tracking to apply to a wide range of applications. This is your secret weapon for beatboxing...



The **EDISON EX1** is the reincarnation of one of our own analog classics. This remarkably effective tool allows manipulation of the stereo field. Selectable Mono or Stereo I/O modes allow the processing, or creation, of Mono/Stereo recorded sound sources. (Inspired by BEHRINGER EDISON)


Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



The **SOUND MAXER** restores natural brilliance and clarity to any audio signal by adjusting the phase and amplitude integrity to reveal more of the natural texture of the sound, which is often hidden when using some effects and equalizers. (Inspired by Sonic Maximizer 482i*)



The **DIMENSIONAL CHORUS** is the perfect emulation of what has been referred to as “the best analog Chorus unit ever created”. Four simple Mode preset buttons activate amazing effects, best described as “space” and “dimension”. Absolutely faithful to the original, multiple preset buttons can be pressed simultaneously. (Inspired by Roland Dimension D Chorus*)



MODULATION DELAY combines three of the most-used time modulation effects into one easy-to-operate unit. Enjoy true-stereo delay with a lush and spacious chorus, topped off with your choice of three very unique reverb models, Ambience, Club and Hall.

Digital Mixers

MR18


18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



ENHANCERS let you emphasize the Bass, Midrange and Hi output at selectable frequencies, allowing you to generate maximum punch, clarity and detail – without turning up the overall volume. (Inspired by SPL Vitalizer*)



EXCITERS increase presence and intelligibility in live sound applications, and are indispensable for adding clarity, air and harmonic overtones in the studio. (Inspired by Aphex Aural Exciter*)



Unlike typical graphic EQs, our **STEREO TruEQ** delivers the exact frequency response for the new fader setting, taking neighboring fader settings into account – for surgical and responsive filtering or general room equalization (Modeled after BEHRINGER UltraCurve DEQ2496). The MR18 can provide up to 16 mono graphic EQs – one in each of the 6 Aux Buses and Main LR, plus 8 additional mono GEQ effects (4 stereo) that may be inserted into channels.

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



VINTAGE ROOM stands out head and shoulders over other competing reverberation strategies in the way it models sound propagation in the air and room resonances. Invented in the early '80s, the role model delivered authentic room character from an algorithmic reverb long before convolution-based processing was available. It is an ideal reverb for mixes or sub-groups, as it adds space to complex signals – highly valued in classical music and broadcasting environments. (Inspired by Quantec QRS*)



PLATE REVERB emulates the characteristics of a plate reverb chamber with control over the damping pad, modulation depth and speed, and crossover. This classic effect will give your tracks the sound heard on countless hit records since the late 1950s. (Inspired by Lexicon PCM70*)




The **3-TAP DELAY** in the M32 records the input signal and then echoes it back after a user-definable period of time and number of repeats. What makes the stereo and triple delay useful and outstanding is the linked tap-timing and musical choice of echo patterns. Use the 3-TAP DELAY to fatten up vocals and instruments, or to add an enhanced spatial element to any performance.

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



The **HALL REVERB** effect provides a broad spectrum of reverberation possibilities, from small room to large, or even cavernous proportions. When softly mixed with the original signal, Hall Reverb can be used to create a warm, more natural sound. (Inspired by Lexicon 480L*)

The Lexicon 480L* has been recognized as the gold standard of digital reverb. In addition to the Hall Reverb program, we have included four more of the finest reverb models: Ambience, Rich Plate, Room and Rich Chamber. These models precisely capture all nuances based on our "True Physical Modeling", and our algorithms even incorporate the unit's AD/DA gain stepping converters – nailing the entire analog and digital circuit paths right down to the last detail. (Inspired by Lexicon 480L*)



This handy dynamic **FLANGER & DELAY** duo blends the "whoosh" of soaring jet planes with classic Delay, and can be adjusted from mild to wild. This combination effect only takes up one FX slot. (Inspired by Lexicon PCM70*)




WAVE DESIGNER is a powerful tool for adjusting signal transients and dynamics such as attack and sustain. Use it to make a snare drum really "crack" in the mix or level out volume inconsistencies of slap bass tracks. (Inspired by SPL Transient Designer*)

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



The **STEREO PRECISION LIMITER** is perfect for setting a precise volume limits, ensuring distortion-free and optimal signal integrity. Use the Stereo Precision Limiter to boost quiet signals or reduce the level of “hot” signals to prevent clipping. (Inspired by Sony Oxford Dynamics*)



The **DE-ESSER** is a “must-have” tool for reducing the amount of sibilance in vocal mics while adeptly preserving the natural voice timbre of a performance. Use it to enhance the smoothness of the upper mid to high frequencies in vocals as well as drum overheads and strings, etc. (Inspired by SPL 1219*)

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface





Based on the legendary EMT250, the **VINTAGE REVERB** delivers a shimmering, bright reverb that will not drown out or overpower your live/recorded tracks. Use the **VINTAGE REVERB** to sweeten vocals and snare drums without sacrificing clarity. (Inspired by EMT250 Plate Reverb*)



Taking up only one FX slot, the **CHORUS & CHAMBER** effect combines the shimmer and doubling characteristics of a studio-grade Chorus with the sweet sound of a traditional Chamber reverb. (Inspired by Lexicon PCM70*)

18-Input Digital Mixer for iPad/Android Tablets with 16 MIDAS PRO Preamps, Integrated Wifi Module and Multi-Channel USB Audio Interface

Switch between the Large RTA view, displaying any available signal in full screen resolution, or the Combined RTA view shown above each of the channel and bus EQ curves – and see the results of your filtering choices. Additionally, the RTA can be displayed on top of the 31-band graphic EQs in the Main LR or Aux buses. Monitoring and controlling frequencies has never been easier!



MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

16 Channels of Personal Monitoring

The easy way to send sound, Behringer's proprietary ULTRANET connectivity allows you to send 16 digital sources over a lightweight and easy-to-deploy Cat 5e cable to [P16-D Digital ULTRANET Distributors](#), or directly to [P16-M Personal Monitor Mixers](#). This powerful and advanced technology makes it easy for individual performers to create their own "more me" mix – and frees you to put on your best show. ULTRANET also provides the perfect conduit for sending your mix to the new [TURBOSOUND iQ Series](#) loudspeakers, which can tap into the 16-channel digital bus directly.



MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

Uncompromised Channel Processing

The MR18 allows you to achieve the same incredible level of EQ finesse as the award-winning M32 thanks to its 100-band Real Time Analyzer, which is built into every input channel and bus EQ. Visual feedback built into the control app allows you to see and make fast, surgical adjustments to frequencies in need of a boost or a cut. You will wonder how you ever EQ'd without it!

Every input channel also features Low-Cut, 4-band fully parametric EQ and the same Gate and Compressor dynamics suite found in the M32 – with one very special addition; you can choose either Expert or Simple functionality. In Expert mode, you can drill down and take total control over every nuance of your dynamics. Or, if you are more of the 'plug and play' type, Simple mode lets you either select from one of 4 carefully-optimized presets – or load your own channel templates. Add to this 40-Bit, floating-point DSP and you will experience virtually "unlimited" dynamic range with no internal overload and near-zero overall latency.

In addition to the Main L/R bus for Front of House, 6 Aux buses are provided for dialing in the perfect monitor mixes, or creating a dedicated mix for your USB stereo recording – complete with inserts, dynamics, and either a 6-band parametric EQ or 31-band graphic EQ. And if you want even more precise control over your EQ, 100-band RTAs are available for all of these buses, too.



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

MIDI In/Out for Live Performance Controllers

The physical MIDI I/O port on the MR18 mixer can also be used for connecting external MIDI controllers, such as [BEHRINGER's X-TOUCH](#) or [B-CONTROL](#) products, for dynamically controlling channel level, muting and panorama adjustments during your performance. The installed firmware also supports the Mackie Control protocol, allowing you to easily apply comprehensive remote editing and parameter adjustments via any compatible MIDI device.



Dedicated Apps and Software – All Platforms Covered

Since we wanted the MR18 to benefit from the best remote apps, we engaged dedicated development teams for the iOS*, Android*, and PC/Linux/Mac* based remote control applications. When you download an M AIR app for your operating system, you can rest assured that you will get the fully optimized experience we intended. Future firmware updates will be available free of charge and add even more professional-grade features, FX "Plug-Ins", and functionality.



Digital Mixers


MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

M AIR EDIT (PC/Mac/Linux)

If your application requires a computer for **MIDAS M AIR** mixer remote control, then M AIR EDIT was made just for you. Simply copy and launch the free software with your computer, connect to the mixer via its built-in Ethernet (LAN) connector using a Cat 5e cable (max. 100 m length) – and all M AIR mixer functions are instantly mirrored on your computer screen. Since a PC screen is larger than the one on your telephone, M AIR EDIT allows the opening and scaling of more app windows, such as routing or FX editing – letting you decide how much information you need at a glance. All touch screens are supported, or you can use a mouse to adjust your physical mixer's settings. You can even control multiple mixers remotely from a single computer, or create several strategically placed computer stations to control the same mixer. With M AIR EDIT, your PC, Linux or Mac computer becomes your virtual mixer – both live and in the studio.

Download the free M AIR EDIT software from midas.com.



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

M AIR MIX for iPad

Front of House is wherever you and your iPad are – thanks to the new M AIR MIX app for iPad. Simply download the free app to your iPad, set the MIDAS M AIR mixer to Access Point mode and connect your iPad to the MR18 network that will show up. After launching the M AIR MIX app, select the mixer image, and all of your M AIR mixer's settings can now be adjusted directly from your iPad. You can save your favorite scenes, and load previously stored scenes and presets to/from your iPad or customize your channel layout – all with the support of innovative drag 'n' drop functionality.

Download the free M AIR MIX App for iPad from the Apple App Store.




MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

M AIR MIX for Android

Designed specifically for all Android mobile devices (2.2 or higher), which includes tablets and smartphones, the app can be used in one of two modes: full access mixing mode; or bound to a specific aux bus for creating personal monitor mixes remotely on MIDAS M AIR mixers. Using this free and easy to learn app, each performer can use their Android device to dial-in the perfect personal IEM or wedge monitor mix, without having to consult the audio engineer for assistance. With the M AIR MIX App for Android, personal monitor mixing just got a whole lot more personal – both live and in the studio! But M AIR MIX offers even more; in full access mixing mode, the app provides control over all channel processing including the RTA overlay, effects editing, storing/loading scenes or presets, and much more – whether you are running a 12" tablet or a 5" smartphone.

Download the free M AIR CUE for Android App from the androidapps.com.



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Superb Value

The feature-packed MR18 is the result of the engineering, manufacturing and application expertise of legendary console manufacturer **MIDAS**, the iconic signal processing genius of **KLARK TEKNIK** – and **MUSIC**'s unique ability to deliver a superior value proposition. MR18's sound quality far surpasses that of competing models, both on paper and in performance. With 18 inputs, 16 MIDAS PRO mic preamps, 6 aux buses, a built-in Wifi router, MIDI I/O, a multi-channel bidirectional USB audio interface, and free downloadable apps for iOS, Android and PC, and a host of other high-end professional features, the M AIR MR18 is equipped to handle your most demanding audio application.

Visit your local dealer and take a closer look at the M AIR MR18 Digital Mixer, or get yours online – today!

You Are Covered

We always strive to provide the best possible Customer Experience. Our products are made in our own **MUSIC Group** factory using state-of-the-art automation, enhanced production workflows and quality assurance labs with the most sophisticated test equipment available in the world. As a result, we have one of the lowest product failure rates in the industry, and we confidently back it up with a generous **3-Year Warranty** program.




Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

Dimensions




with bumper

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

Dimensions



with ear rack

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

Technical Specifications

Processing

Number of processing channels	18 input channels, 4 FX return channels, 6 aux buses, main LR
Internal effects engines	4 true stereo
Signal processing	40-bit floating point
A/D-D/A conversion	24-bit @ 44.1 / 48 kHz, 115 dB dynamic range
Analog I/O latency*	0.8 ms

Connectors

Programmable mic preamps, designed by MIDAS PRO	16 XLR/TRS combo jacks, balanced
Line / Aux inputs, stereo	2 TRS, balanced
Main outputs	2 XLR, balanced
Aux outputs	6 XLR, balanced
Phones outputs	1 TRS
ULTRANET	1 RJ45
MIDI inputs / outputs	1/1 DIN
Ethernet	1 RJ45
Audio/Midi interface	1 USB Type B

Mic Input Characteristics

Preamp design	MIDAS PRO
THD + noise, unity gain, 0 dBu, 1 kHz	0.005%, unweighted
Phantom power, switchable per input	48 V
EIN noise, at +60 dB gain, 150R source	-125 dBu, 22 Hz - 22 kHz unweighted
CMRR, XLR, 1 kHz @ unity gain	Typically 65 dB
CMRR, XLR, 1 kHz @ +60 dB gain	Typically 90 dB

Input/Output Characteristics

Frequency range, @ 48 kHz sample rate, +/- 0.5 dB	20 Hz - 20 kHz
Dynamic range, analog in to analog out	107 dB, 22 Hz - 22 kHz unweighted
A/D dynamic range, preamp to converter	110 dB, 22 Hz - 22 kHz unweighted
D/A dynamic range, converter and output	111 dB, 22 Hz - 22 kHz unweighted
Cross talk rejection @ 1 kHz, adjacent channels	90 dB
Mic/Line 1-16 Input impedance XLR jack, unbal. / bal.	10 kΩ
Non clip maximum input level, XLR	+23.5 dBu
Line 17-18 Input impedance, TRS unbal. / bal.	20 kΩ / 40 kΩ
Non clip maximum input level, TRS	+21 dBu

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

Technical Specifications

Output Characteristics

Output impedance, XLR	50 Ω
Maximum output level, XLR	+21 dBu
Phones output impedance	50 Ω
Maximum phones output level	+21 dBu
Noise @ unity gain, 1 input assigned, XLR and TRS	-86 dBu, 22 Hz - 22 kHz unweighted
Noise when muted, XLR and TRS	-90 dBu, 22 Hz - 22 kHz unweighted

USB Audio/MIDI Interface

Type	USB 2.0, type B
Supported operating systems	Windows 7 or higher**, Mac OS X 10.6.8 or higher, iOS 7 or higher (iPad), Linux
Supported sample rates	44.1 / 48 kHz
I/O audio channels	18 x 18
I/O MIDI channels	16 x 16 (1 port)

WLAN Module

Antenna	External, SMA connector, 50 Ω
Access Point, number of clients	Max. 4
IEEE 802.11 b/g standard	2.4 GHz
Frequency Range	2412-2462 MHz
WLAN channels (Wifi Client, Access Point)	1-11
Max Output Power	19 dBm (802.11 b) / 18 dBm (802.11 g)

Power

Switch-mode power supply	Autorange 100-240 V, (50/60 Hz)
Power consumption	30 W

Physical

Standard operating temperature range	5°C – 40°C (41°F – 104°F)
Dimensions	333 (W) x 149 (D) x 140 (H) mm, (13.1 x 5.9 x 5.8")
Weight	3.9 kg (8.6 lbs)

* including all channel and bus processing, excluding insert effects

** Windows ASIO driver available as download from midasconsoles.com; compatible to CoreAudio on Mac OS X and iOS

***Mac OS X is a trademark of Apple, Inc.

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface

Architecture & Engineering Specifications

The MR18 shall be an 18-input digital audio mixer intended for remote control via iPad/Android/PC mobile applications

The product shall have 16 MIDAS PRO microphone preamplifiers with Neutrik latching XLR/TRS-combo connectors

The product shall have an additional stereo line-level input on two TRS connectors

The product shall have 6 auxiliary outputs plus main Left and Right outputs on Neutrik XLR connectors

The product shall include an integrated WLAN/LAN Module for networked remote control

The product shall have a class-compliant 18x18-channel USB audio interface

The product shall provide automatic mixing and gain sharing for all 16 microphone channels

The product shall include 4 integrated digital effects processors

The product shall be using 40-bit floating point digital signal processing at 44.1 or 48 kHz sample rates

The product shall provide connectivity for Behringer's Ultranet personal monitoring bus

The product shall include rubber protection bumpers and 19" rack adaptors

The processing shall provide dynamics processing plus 6-band parametric or 31-band graphic equalisers on all Main Left/Right and the 6 aux buses

The product shall be operated via free iOS, Android and PC/Mac*/Linux* apps available for remote operation via Ethernet, LAN or WiFi

The product shall have a detachable 2.4 GHz antenna on the front panel

The product shall have a MIDI In and Out for controlling the mixer via MIDI equipment or for use as a USB MIDI interface

The product shall provide a stereo phones output on TRS jack socket with dedicated front panel level control for monitoring

The product shall be fitted with an internal auto-ranging switch mode power supply, capable of operation at AC voltages ranging from 100 to 240 VAC, at 50/60Hz

The mains connector shall be a standard IEC receptacle

The MR18 shall be 331 mm wide x 139 mm deep x 149 mm high (13.1" x 5.5" x 5.9"), with nominal weight 3.9 kg (8.6 lbs)

The product shall be the MIDAS MR18 and no other alternative shall be acceptable

Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



Digital Mixers

MR18

18-Input Digital Mixer for iPad/Android
Tablets with 16 MIDAS PRO Preamps,
Integrated Wifi Module and
Multi-Channel USB Audio Interface



For service, support or more information contact the MIDAS location nearest you:

Europe
MUSIC Group Services UK
Tel: +44 156 273 2290
Email: CARE@music-group.com

USA/Canada
MUSIC Group Services NV Inc.
Tel: +1 702 800 8290
Email: CARE@music-group.com

Japan
MUSIC Group Services JP K.K.
Tel: +81 3 6231 0454
Email: CARE@music-group.com

MUSIC Group accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph, or statement contained herein. Technical specifications, appearances and other information are subject to change without notice. All trademarks are the property of their respective owners. MIDAS, KLARK TEKNIK, LAB GRUPPEN, LAKE, TANNOY, TURBOSOUND, TC ELECTRONIC, TC HELICON, BEHRINGER, BUGERA and DDA are trademarks or registered trademarks of MUSIC Group IP Ltd.
© MUSIC Group IP Ltd. 2017 All rights reserved.

