

Product information:

The LCR700 is a digital LCR measurement appliance, essential for sound and electronic engineers. Measurements can be made for induction, capacitance and resistance and the dissipation factor (D) can be read-out on a second display. It can be set to auto-ranging or manual mode, and all measurements can be carried out on two different frequency's, 120Hz and 1kHz. This allows measurements of great accuracy on all kinds of specimen. An RS232 optical interface is provided to allow communication with a computer, and the Auto-Power OFF function helps to conserve the lifespan of the battery. Supplied with: RS232 PC connection cable, test leads, shock absorbing cover, software, instruction manual.



System specifications:

Power	Consumption	0.75 W (max.)
Test frequency		1 kHz and 120 Hz
Measurements parameters		Ls+(Q, D, Rs), Lp+(Q, D, Rp)
		Cs+(Q, D, Rs), Cp+(Q, D, Rp)
Basic accuracy		0.5% for Resistance
		0.7% for Inductance, Capacitance
Display	Type	C\N-4 ½ digits, max. reading of 19999
		\D\N-4 digits, max. reading of 9999 (Auto range)
Measuring range control		Auto & manual
Measuring speed		Approx. 1x/second, nominal
Auto-Power		Auto Power off if not used for 5 minutes
Protective fuse		0.1A fast-blow 250V AC
Resolution		Resistance up to 0.001Ω
		Inductance Capacitance up to 0.1uH/0.1pF
Power	Supply	9 V DC Battery

Product Features:

External Power supply	Adapter min. 12 V to max. 15 V	
Dimensions	91 x 192 x 52.5 mm (W x H x D)	
Weight	0.365 kg	
Accessories	Included	Test leads
		Instruction manual
		Spare fuse in meter
		RS-232 connection cable
		Shock absorbing cover

Shipping & Ordering:

Packaging	Cardboard box
Shipping weight & volume	0.365 kg - 0.00091 Cbm