

PLE-WP3S2Z-EU Wall Panel

www.boschsecurity.com



BOSCH

Invented for life



- Can be used for all Plena Easyline (PLE) mixer-amplifiers
- Remote selection of three music source inputs
- Remote zone selection
- Perfect companion to Bosch volume controls
- Daisy-chain of multiple wall panels

The Plena PLE-WP3S2Z-EU Wall Panel is used to remotely select a music source and activate or deactivate zones of a Plena PLE audio mixer or mixer amplifier.

Functions

Remote zone and input source control

Two zones and three music input sources can be controlled from a remote location by selecting the individual switches.

Indicators

The ON status of each zone and selected music source is indicated by an LED.

Connections and settings

With the use of CAT-5 cable and RJ-45 connector the PLE-WP3S2Z-EU Wall Panel can be easily and quickly connected to the PLE series mixer or mixer amplifier. Settings are not required.

Daisy chain / Remote locations

Maximum four PLE-WP3S2Z-EU Wall Panels can be daisy chained to remotely control a PLE series mixer or mixer amplifier.

Certifications and approvals

Safety	acc. to EN 60065
EMC emission	acc. to EN 55103-1
EMC immunity	acc. to EN 55103-2

Region	Certification
Europe	CE

Installation/configuration notes

The Wall Panel is installed to the mixer or mixer-amplifier via standard CAT-5 cable with RJ-45 connector. The maximum cable distance is 200 m. The design and color are unobtrusive in any interior. Ease of installation, operation and reliability is optimized in the design. The appearance is matched to the Bosch Loudspeaker Volume Controls.

The wall panel buttons have the same function as the corresponding buttons of the Plena mixer front panel

Parts included

1	PLE-WP3S2Z-EU Wall Panel
1	Quick Reference Card

Technical specifications**Electrical**

Power supply	
Voltage range	5 VDC, supplied by the connected amplifier
Current consumption (typical)	<50 mA
Connectors	
to (mixer) amplifier	1 x RJ-45
Loop through	1 x RJ-45

Mechanical

Dimensions (H x W x D)	87 x 87 x 21 mm (3.43 x 3.43 x 0.83 in)
Weight	Approx. 0.35 kg (0.77 lb)
Color	White
Label text color	Silver

Environmental

Operating temperature	-10 °C to +45 °C (14 °F to +113 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

Ordering information**PLE-WP3S2Z-EU Wall Panel**

Wall panel for remotely selecting a music source and activating or deactivating zones of an audio mixer or mixer amplifier.

Order number **PLE-WP3S2Z-EU**

Represented by:**Americas:**

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com