# BRX325SP

### Modular Portable Line Array Subwoofer with 6-Channel Amplifier





#### **HIGHLIGHTS**

#### **Superior JBL Acoustics out of the Box**

Professional JBL performance with high SPL capabilities; easy-touse rigging hardware, built-in amplification and plug-and-play DSP for easy setup

#### **Modular & Scalable Configuration Options**

System can be expanded as needed, with each subwoofer capable of powering up to 4 BRX308-LA Line Array Elements

#### Portable & Rugged

Includes casters for easy transport; tour-tested cabinets feature all-wood construction with a Duraflex coating that protects against wear and tear

The BRX300 Series is a versatile line array for bands, DJs, rental firms, houses of worship and anyone who needs a compact, portable system that provides superior fidelity, high output and consistent coverage in a range of sound-reinforcement scenarios.

The modular BRX300 Series makes the power of line array technology accessible to customers who are not trained audio engineers, thanks to its plug-and-play simplicity, built-in corrective signal processing, smart transport system and hassle-free rigging hardware. Deploy in minutes and enjoy optimal sound out of the box with components engineered for fidelity and ease of use.

For decades, the world's top entertainment venues and touring productions have relied on the superior power and clarity of JBL Professional line array technology; now it's easier than ever to bring that legendary sonic performance to small and mid-size productions.

#### **KEY MESSAGES** ■

#### **LEGENDARY JBL TOUR SOUND**

The BRX325SP Powered Subwoofer draws from JBL's legendary touring technologies to deliver class-leading SPLs while reproducing every sonic detail with superior depth and clarity, thanks to proprietary drivers that are engineered for maximum performance matched with the BRX325SP's built-in amplifier.

#### **POWER THAT PACKS A PUNCH**

You don't need to sacrifice power for size: the BRX325SP Powered Subwoofer delivers 136 dB SPL and offers six channels of built-in amplification—the highest channel count in its class—effortlessly powering up to four BRX308-LA Line Array Elements.

#### **VERSATILE, VARIABLE COVERAGE**

The BRX300 Series can scale to accommodate any small or midsize application. Systems can be configured in the following ways:

- One subwoofer and two tops, stacked or pole mounted
- One subwoofer and four tops, stacked
- Two ground-stacked subwoofers with eight tops flown
- One flown subwoofer with four adjacent tops flown

#### TAKE THE GUESSWORK OUT OF SYSTEM SETUP

The BRX300 Series delivers performance you can count on, right out of the box. The BRX325SP's sophisticated internal processing handles crossover management, EQ, limiting, correction filters, phase processing and driver protection, so you can focus less on system calibration and more on your mix.

#### **SYSTEM COMPONENTS**

BRX325SP Powered Subwoofer

# BRX325SP



## Modular Portable Line Array Subwoofer with 6-Channel Amplifier

### **APPLICATIONS**

Live music events, receptions, corporate functions and house-of-worship services in small to midsize venues

#### FEATURES

- · Dual 15-inch woofers
- 136 dB maximum SPL
- Built-in DSP includes crossover management, EQ, limiting, correction filters, phase-corrected processing and driver-protection circuitry
- Integrated 1,000 watt-per-channel, 6-channel amplifier offers the most channels in its class
- Powers up to four BRX308-LA Line Array Elements

- Dual inputs with Input Y mode allow a single input for the subwoofer and tops or dedicated inputs for more advanced uses
- Supports ground stacking of up to four BRX308-LAs, or a single BRX325SP can be flown using the optional BRX308-AF Array Frame
- Casters provide ease of transport
- · Power cable options for China, India and APAC regions

#### **ACCESSORIES**

 $\textbf{BRX308-ACC} - \text{Accessory kit including transporter and lid} \ \ \text{for} \ 4 \times \text{BRX308LA}, \ \text{padded cover for transporter and BRX325SP}, \ \text{speaker cables}$ 

BRX308-AF - Array frame to suspend BRX325SP or 8 x BRX308-LA

BRX308-PM - Pole and adapter to mount 2 x BRX308-LA on BRX325SP subwoofer

#### **TECHNICAL SPECIFICATIONS** ■

SYSTEM TYPE: Modular, portable line array subwoofer

**FREQUENCY RANGE (-10 dB):** 32 Hz–250 Hz **AMP INPUT MODES:** Dual, Input Y

**INPUT:** Two balanced XLR-F wired in parallel to XLR-M for THRU

outputs

**OUTPUT:** Two 4-pole NL4 connectors for

powering up to four tops

CROSSOVER: Internal DSP incl. FIR processing
SYSTEM POWER: 6 channels @ 1000 watts each

MAX PEAK SPL (2 PI):136 dBTRANSDUCERS:2 x 15"COMPLIANCE:CEMATERIAL:Plywood

**COLOR/FINISH:** Matte black, Duraflex

**POWER INPUT:** 20A powerCON/230 VAC only

WEIGHT: 86 kg (190 lb)

DIMENSIONS (D x W x H): 693 x 680 x 890 mm (27.3 x 26.7 x 35 in) (excludes caster wheels)

#### **ORDER SPECIFICATIONS**

**BOX DIMS (L x W x H):** 960 x 920 x 800 mm (37.8 x 36.22 x 31.5 in)

**SHIPPING WEIGHT:** 98 kg (216.05 lb)

**COUNTRY OF ORIGIN:** CN

**UPC CODE:** 691991034046



HARMAN Professional 8500 Balboa Blvd. Northridge, CA 91329 USA

© 2020 HARMAN International Industries, Incorporated. All rights reserved. Features, specifications and appearance are subject to change without notice.

www.jblpro.com