

marantz



SR8015

Marantz SR8015 11.2ch 8K AV receiver with 3D Audio, HEOS® Built-in and Voice Control

Enjoy exquisitely detailed home cinema with the Marantz SR8015 11.2 channel 8K UHD AV receiver. Delight in the most musical sound for any source — from home theater, to vinyl, to digital streaming. Completely immerse yourself in movies and TV with elevated surround sound formatting from Dolby Atmos®, DTS:X®, DTS:X® Pro, IMAX® Enhanced and Auro-3D®. Enjoy seamless voice control from the leading voice agents, multi-room connectivity and the latest in HDMI technology.

- Premium, power performing amplification: Delivers a masterful 140W per channel (8 ohms, 20Hz-20kHz, THD: 0.05%, 2 ch. driven) so you experience your entertainment in remarkable detail.
- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices. Showcasing one dedicated 8K input and two outputs, enjoy 8K/60Hz or 4K/120Hz pass-through in amazing clarity. 8K upscaling is available on all eight HDMI ports.
- Featuring the most advanced object-based audio formats: Dolby Atmos®, Dolby Atmos Height Virtualization Technology, DTS:X®, DTS Virtual:X™, DTS:X® Pro, IMAX® Enhanced and Auro-3D® processing are all supported to allow you to listen to all of your favorite audio styles.
- DTS:X® Pro support: Available in a future firmware update, DTS:X® Pro is capable of processing up to 13 channels, wowing listeners with the most cutting edge DTS technology.
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV via eARC HDMI to allow uncompressed and object-based audio formats like Dolby Atmos® and DTS:X® directly from your smart TV app to your AV receiver.
- Bringing you the latest in video compatibility: The latest HDR format support including HDR10, HDR10+ (New in 2020), HLG, Dolby Vision, 4:4:4 color resolution and BT.2020, as well as Dynamic HDR (New in 2020), to provide miraculous picture quality for brightness, clarity and contrast.
- Experience the next scene in movie entertainment: With 8K/60Hz pass-through or upscaling, Dynamic HDR and Quick Media Switching (QMS), enjoy the most crystal clear and smoothest picture quality available.
- The latest in gaming thrills: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), enjoy your gaming experience with amazing imaging with reduced lag and tearing.
- Stream music from your favorite sources: Play songs from Spotify, Pandora, TIDAL and more via AirPlay 2, Bluetooth, Wi-Fi and the HEOS app. (Music streaming services may vary by region)
- Supports all your favorite voice assistants: With the SR8015, simply use your voice to control your preferred voice assistant like Amazon Alexa, Google Assistant, Apple Siri, and Josh.ai for hands free enjoyment.

Modern Musical Luxury

Dolby Atmos

DTS

DTS VIRTUAL

DTS X PRO

IMAX ENHANCED

AURO 3D

8K UHD

HDMI

Dolby VISION

HDR10+

isf

HEOS BUILT-IN

WORKS WITH alexa

works with Hey Google

JOSH

Works with Apple AirPlay

Bluetooth

WiFi CERTIFIED

AUDYSSEY MULTIDIMENSIONAL DYNAMIC VOLUME

AUDYSSEY LFC

Hi-Res AUDIO

HDAM

room tested

iHeartRADIO

Spotify

pandora

amazon music HD

TIDAL

MUSIC

TUNE IN

DEEZER

napster

SOUNDCLOUD

(SiriusXM)

domotz

ORC

SR8015

Technical Specs



Multichannel surround		
DTS HD Master / DTS:X / DTS:X Pro	• / • / •	
DTS Neo:X / DTS Neural:X	- / •	
DTS Virtual:X	•	
IMAX Enhanced	•	
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization	• / • / •	
Dolby ProLogic IIz / Dolby Surround	- / •	
Auro 3D	•	
Multichannel Stereo	•	
Max Number of Processing (Preamp) Channels	13.2	
Sound Enhancements		
Discrete Power Amplifier	•	
Copper Plated Chassis	•	
Power Transformer: Toroidal / EI	Toroidal	
Current Feedback Topology	•	
Hyper Dynamic Amplifier Modules (HDAM)	•	
Pure Direct	•	
Gold Plated RCA Terminals	•	
Clock Jitter Reducer	•	
Audyssey	MultEQ XT32	
Audyssey Dynamic EQ / Dynamic Volume	• / •	
Audyssey LFC	•	
Compressed Audio Enhancer: MDAX2	•	
Network		
HEOS Multi-room and Streaming	•	
Bluetooth Re-transmit for Bluetooth headphones	•	
Alexa / Google Voice Assistant / Apple HomePod	• / • / •	
Network Audio Sharing	•	
Lossy Formats: MP3 / WMA / AAC	• / • / •	
Lossless Formats: FLAC / ALAC / WAV	• / • / •	
Lossless formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •	
DSD Audio Streaming	• (2.8/5.6MHz)	
FLAC HD 192/24	•	
WAV 192/24	•	
ALAC 192/24	•	
Gapless Playback	• (FLAC, WAV, ALAC, DSD)	
AirPlay Audio Streaming	• (AirPlay2)	
Internet Radio	• (TuneIn)	
Spotify*	• (connect)	
Pandora	•	
SiriusXM	•	
Other Streaming Services *	Amazon Music HD / TIDAL / Deezer / iHeart Radio / Napster / Soundcloud / Mood Mix	
Compatible with Remote APP for Smart Phones	Marantz 2016 AVR Remote	
Compatible with Remote APP for Tablets	Android / iOS / Amazon Kindle	
Ethernet Ports	•	
Wi-Fi	•	
Bluetooth	•	
HDMI		
HDMI Inputs: Back / Front	7 / 1	
HDCP2.3 support	•	
HDMI Outputs: Main / Zone	2 / 1	
Video Conversion Analog -> HDMI	•	
Analog to HDMI scaling	480i/576i up to 8K 60/50	
HDMI to HDMI scaling	up to 8K 60/50	
GUI Overlay on HDMI	•	
8K/60Hz / 4K/120Hz	• / •	
3D / 4K / CEC / ARC	• / • / • / • -	
Enhanced ARC	•	
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR	• / • / • / • / •	
ALLM (Auto Low Latency Mode) Pass-through for gaming	•	
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching	• / • / •	
3D Signal Pass-Through	•	
8K signal pass-through / scaling / GUI overlay	• / • / •	
4K Signal Pass-Through / Scaling / GUI Overlay	• / • / •	
HDMI Pass-Through in Standby Mode	•	
Picture Adjust / Noise Reduction	• / •	
CEC	•	
DSD Audio Capability	•	
Audio Return Channel	•	
Auto LipSync	•	

Multiroom / CI		
HEOS Multi-Room Integrated	•	
HEOS Link Compatibility: IR/ IP	• / •	
Multi-Room zones	3	
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog	• (2ch) / • (2ch) / • / •	
Zone Audio Output: Speaker / Preout	• / •	
Zone HDMI Output from HDMI Source	•	
IP Control / RS232 Control / Web Control / App Control	• / • / • / •	
IR Flasher In	•	
Marantz Remote Bus	•	
DC Trigger Output	2	
HDMI Diagnostics	•	
Others		
Auto Speaker Setup by Microphone	Audyssey MultEQ XT32	
FL Display	2 lines + Port Hole	
Graphic User Interface - GUI	Advanced	
ISF Certification	•	
GUI Languages	3	
Setup Assistant	•	
Smart Select	•	
Firmware Update by Network / USB	• / •	
Variable Cross Over	•	
Optimized Bass Redirection	•	
Bass Sync	•	
ECO Mode	•	
Auto Power Off	•	
Sleep Timer	•	
Video Inputs/Outputs		
Composite In / Out	4+1 / 2	
Component In / Out	3 / 1	
HDMI In / Out	7+1 / 3	
Multi-Room Video Out: Video / HDMI	• / •	
Audio Inputs/Outputs		
Analog In / Out	6+1 / -	
Phono (MM) In	•	
Digital In: Optical / Coaxial	2 / 2	
Multi-Room Out: Analog / Digital	2 / -	
Multichannel Pre Out	• (11.2)	
Subwoofer Out	2 (independant)	
7.1 Multichannel Input	•	
Other		
Speaker Terminal: Gold Plated Screw / Regular Screw	• / -	
Number of Speaker Terminals	13	
Speaker A / B	assignable	
Bi-Amp Drive	assignable	
Multi-Room Speaker Terminal	assignable	
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	• / • - / • / •	
USB Audio / Made for iPod / Made for iPhone	• / - / -	
AM/FM Tuner	•	
General Power		
Number of Poweramps	11	
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)	140 W	
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)	175 W	
Power Output (6 ohm, 1 kHz, 10% 1ch Drive)	250 W	
70% Guarantee	•	
General		
Metal Front Panel	•	
System Remote Control	RC045SR	
Pre-Programmed / Learnable / LCD Display	• / • / •	
Power Consumption in W	780	
Power Consumption No-Sound (ECO on / off) in W	65 W / 110 W	
Standby Consumption in W	0.2	
CEC Standby Consumption in W	0.5	
Network Standby Consumption in W	3.5	
Maximum Dimensions		
Antenna/Horizontal:(W x D x H)	17.3 x 18.1 x 7.3	
Antenna/Vertical:(W x D x H)	17.3 x 18.1 x 9.8	
w/o Antenna:(W x D x H)	17.3 x 17.7 x 7.3	
Weight in LBS	38.4	

Design and specifications are subject to change by Marantz without notice.

The Bluetooth* word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

www.marantz.com